



MILWAUKEE RESISTOR GRID RESISTOR QUICK SELECT

Use the following grid resistor quick select cross-reference to conveniently select grid resistors for your specific application. Simply locate the manufacturer's column and part number for the grid resistor you are replacing. The corresponding Milwaukee Resistor replacement is located in the far left column on the same line.

Milwaukee Resistor Part Number	Total Ohms at 25C +/- 10%	Continuous Amps at 375C	SUGGESTED REPLACEMENT FOR							
			GE	Post Glover	Cutler Hammer	Hubbell	Westinghouse	Square D	Challenger	IPC
MRCG-8	0.074	350		PG8		53357-003		TW280D		SSR350
MRCG-9	0.088	300		PG9						
MRCG-10	0.1	300	IC9141-A002A103	PG10		53357-002				SSR300
MRCG-11	0.115	260		PG11	G11WL12	53357-001		TW220D		SSR260
MRCG-12	0.144	225		PG12		53357-023				SSR225
MRCG-13	0.16	185	IC9141-A001A101	PG13	G11WL16					
MRCG-14	0.182	185		PG14				TW180D		
MRCG-15	0.217	185		PG15	G11WL20	53357-022				SSG190
MRCG-16	0.245	165	IC9141-A001A102	PG16	G11WL25		1776163	TW150D	112A155	SSG160
MRCG-17	0.277	150		PG17		53357-021			112A140	
MRCG-18	0.324	135		PG18	G11WL32	53357-020	1776164	TW120D		
MRCG-19	0.36	135		PG19		53356-023				SSG135
MRCG-20	0.416	120	IC9141-A001A103	PG20	G11WL40	30856-022			112A120	
MRCG-21	0.478	120		PG21	G11W350	30856-021	1776165	TW100D	122A110	SSG120
MRCG-22	0.552	110		PG22		30856-017				
MRCG-23	0.648	100	IC9141-A001A104	PG23	G11WL62	30856-016	1776166	TW85D	112A90	
MRCG-24	0.756	90		PG24	G11WL80	30856-015	1776167			
MRCG-25	0.9	80		PG25						
MRCG-26	1	80		PG26	G11WL100	30856-011	1776168	TW72D	112A75	
MRCG-27	1.2	80	IC9141-A001A205	PG27	G11WL125	30856-010	1777576			SSG83
MRCG-28	1.4	75		PG28		30856-009		TW62D	112A63	SSG75
MRCG-29	1.55	70		PG29	G11WL160	30856-007	1776169			
MRCG-30	1.8	70	IC9141-A001A206	PG30						SSG70
MRCG-31	2.13	63		PG31	G11WL200	30856-006	1777487		112A53	SSG63
MRCG-32	2.6	50	IC9141-A001A207	PG32	G11WL250		1776179	TW50D		
MRCG-33	3.22	44		PG33	G11WL320				112A44	
MRCG-34	3.97	44	IC9141-A001A208	PG34	G11WL400		1776180	TW42D	112A38	SSG42
MRCG-35	5.1	38		PG35	G11WL500		1776181	TW37D		SSG38
MRCG-36	6.59	30	IC9141-A001A209	PG36	G11WL625		1776182	TW32D	112A24	
MRCG-37	8.06	28		PG37	G11WL800		1776170		112A32	
MRCG-38	10.08	25	IC9141-A001A210	PG38			1776183	TW27D		SSG25
MRCG-39	12.24	20		PG39						
MRCG-40	14.69	18		PG40	G11WL1440		1776184	TW21D		
MRCG-41	20.08	13.2		PG41						
MRCG-42	26	12		PG42						
MRCG-43	32.89	10.261		PG43						
MRCG-44	41.76	9		PG44						

* Standard MRCG resistor banks are 26.5"L x 12"D x 6"H

For additional assistance or information, contact Milwaukee Resistor Corporation at:

Milwaukee Resistor Corporation

8920 West Heather Avenue

Milwaukee, WI 53224

Tel: 888-616-6666

Fax: 414-362-9876

Email: sales@milwaukeeeresistor.com

Internet: www.milwaukeeeresistor.com